

## D-LX 201

### Compact flame monitor

Optical flame monitoring in complex multi-burner plants

- Wide dynamic range of five orders of magnitude
- Fully certified to EN 61508 1-7 up to SIL 3
- Real-time analysis of flame stability



## Features

- **Very large temperature range**  
Deployable without change, certified and without need of accessories for isolation, heating or cooling
- **Wide dynamic range**  
Automatic gain adjustment to brightness of flame
- **Consistently two-channel**  
Highest security with simultaneous high availability
- **Ideal support for Functional Safety**  
Safety chains in high demand mode or low demand mode up to SIL 3
- **Extensive certifications**
- **Local display**  
Operational status, settings and flame intensity visible at a single glance, for entire temperature range and all variants
- **Real-time information flame stability**  
Optional continuous qualification of flame stability during operation

## Technical data

<b>Spectral sensitivity</b>	UAF: 280 ... 410 nm UA: 190 ... 520 nm IG: 780 ... 1800 nm
<b>Operating mode</b>	Intermittent and continuous operation
<b>Functional Safety</b>	Self-monitoring and fail-safe, supports safety chains up to SIL 3 (high demand mode/low demand mode)
<b>Switching thresholds</b>	Flame intensity and flicker frequency
<b>Local display</b>	LEDs, always visible at a single glance for all versions; display flame intensity via flash frequency
<b>Flame failure detection time (FFDT)</b>	1, 2, 3, 5 s (separately adjustable for each Range)
<b>Flame ON/OFF contact</b>	Normally open: active when flame ON
<b>Ready-for-operation contact</b>	Normally open: active when no error
<b>Switching capacity</b>	Relay contacts: Max. 24 V $\overline{\text{=}}$ , 0.5 A
<b>Analogue output</b>	0/4 ... 20 mA (configurable), output signal selectable Load max. 750 Ohm
<b>Opening angle</b>	6°
<b>Real-time information</b>	Flame stability analysis (optional)




## Benefits

- **Safe process control**  
Even with strong and fast load changes of firing system the process can be safely managed with flame stability analysis, timely reactions are possible
- **Increased load and fuel flexibility**  
Excellent selective monitoring and stability information allows operation of plant in less stable regimes
- **Protection against unscheduled burner shutdown**  
Burner-specific information on stability allows decisions on preventive maintenance of burners
- **Meeting special requirements**  
Flexible default pre-settings for different combustion situations and fuels
- **Same technology for the most variable application conditions**  
Same product family can be used for most different geographical regions and based on varying systems of standards




<b>Electrical data</b>	24 V $\overline{\text{=}}$ , 5 W, PELV
<b>Ambient conditions</b>	-40 ... +85 °C
<b>Degree of protection</b>	IP66/IP68, NEMA 4X IP65, NEMA 4X (/MP3) IP66, NEMA 4X (Ex versions)
<b>Connections</b>	Sight tube G 1¼" or NPT 1¼", F Purge air G ½" or NPT ½", F
<b>Dimensions</b>	Housing P2 80 x 80 x 250 mm Housing M5 100 x 100 x 260 mm Housing M4 Ø 120 mm, length approx. 310 mm
<b>Weight</b>	Housing (without cable) P2 approx. 0.9 kg M5 approx. 1.2 kg M4 approx. 2.8 kg

<b>Explosion protection</b>	<b>D-LX 201/721 ../M4/84Ex</b> II 2G Ex db IIC T6 or T5 Gb II 2D Ex tb IIIC T85 °C or T100 °C Db
	<b>D-LX 201/721 ../M4/85Ex</b> Cl. I, Div. 1, Gr. A, B, C, D T6/T5 Cl. II, Div. 1, Gr. E, F, G T6/T5; Cl. III
	<b>D-LX 201/721 ../M5/86Ex</b> Cl. I, Div. 2, Gr. A, B, C, D T6/T4 Cl. II, Div. 2, Gr. E, F, G T6/T4; Cl. III
	<b>D-LX 201/721 ../M5/87Ex</b> II 3G Ex nA nC IIC T6 or T4 Gc II 3D Ex tc IIIC T85 °C or T135 °C Dc

D-LX 201 COMPACT FLAME MONITOR FOR DIRECT VIEW | CONFIGURATION OF ACCESSORIES FOR MOUNTING



D-LX 721 COMPACT FLAME MONITOR | USE WITH FIBRE OPTIC SYSTEM



**DURAG GROUP**

**DURAG GROUP**  
Kollastrasse 105  
22453 Hamburg, Germany  
Phone +49 40 554218-0  
Fax +49 40 554254  
info@durag.com

[www.durag.com](http://www.durag.com)